

MQTT Configuration

As of Firmware x.1311 onwards, we have added several more MQTT configuration parameters that can currently be configured through the INI located in /config/mqtt.ini.

In the [config] section you can set the following key/value pairs:

Key	Value
enabled	1 or 0 to enable/disable MQTT
debug	1 or 0 to enable/disable debug logging
mqtt_keepalive	Keepalive at connect - setting to 0 causes issues on some mosquitto installs
mqtt_timeout	Connect timeout in seconds before raising an error
mqtt_port	Remote port number (usually 1833)
mqtt_protocol	Protocol shared during connect. Can be 3 for MQTT v3.0 or 311 for MQTT v3.1.1
enabled	1 or 0 to enable/disable TLS security
mqtt_id	Connect ID. If it's blank the MAC address will be used
mqtt_server	Server host name
mqtt_user	MQTT connect username
mqtt_password	MQTT connect password

From:

<http://wattmon.com/dokuwiki/> - **Wattmon Documentation Wiki**

Permanent link:

http://wattmon.com/dokuwiki/how_tos/mqtt_configuration

Last update: **2024/04/05 05:05**

