

sys_set

FW >= 1300

Set a system parameter

Description

```
int sys_set ( string $parameter , int $value )
```

This function will set an internal parameter

Parameters

\$parameter: The \$parameter must be one of the following:

Parameter	Description
force_log	Set to 1 to trigger a log event
FLASH_WP	Set to 1 to write protect the flash, and 0 to allow writes

Note

The parameters are case sensitive - not all parameters will be available, depending on the hardware (i.e. Flash may not be onboard).

Return Values

Examples

```
<pre><?
// this will fail on the flash drive as it is locked by default at boot

ini_set("1:/config/myinifile.ini","config","value",1);

// unlock flash
sys_set("FLASH_WP",0);

// this will succeed
ini_set("1:/config/myinifile.ini","config","value",1);

// re-lock
sys_set("FLASH_WP",1);
```

```
?></pre>
```

From:

<http://wattmon.com/dokuwiki/> - **Wattmon Documentation Wiki**

Permanent link:

http://wattmon.com/dokuwiki/uphp/functions/sys_set

Last update: **2024/07/16 03:41**

