

pin_set

WMPRO FW >= 1.0 WMMEGA FW >= 2.0

Set a digital output to **value** 1 or 0

Description

pin_set (int \$pin_index, int \$value)

Parameters

\$pin_index: The internal pin number. Refer to [pin_configure\(\)](#) for the list of available pins. If the pin is not configured as a digital output this function does nothing.

\$value: 1 or 0 to set the digital output on or off

Return Values

None

See Also

[pin_configure\(\)](#) - Configure an IO pin as a digital input, output, or analog input

[pin_get\(\)](#) - Return the value of an IO pin

[adc_read\(\)](#) - Read an onboard ADC channel

From:

<http://www.wattmon.com/dokuwiki/> - **Wattmon Documentation Wiki**

Permanent link:

http://www.wattmon.com/dokuwiki/uphp/functions/pin_set?rev=1495210975

Last update: **2021/09/13 05:56**

